ET803

DIGITAL EARTH TESTER

- Measuring earth resistanceby constant current inverter 800Hz approx. 2mA, earth voltage by rectifier type 5k Ω/V approx. 40~500Hz
- Batteries operated always ready for use on site
- 2000 counts LCD display with backlit, data hold



 $\label{eq:constraint} \begin{array}{l} \underline{\text{Technical specifications}} \\ \text{Earth resistance: } 20/200/2000\,\Omega\,,\,\pm2\% \\ \text{Earth voltage: } 200V\,AC\,,\pm2\% \\ \text{Dimensions: } 200X140x60mm \\ \text{Battery: } 1.5Vx6\,,AA\,size \\ \text{Weight: approx. } 700g \end{array}$





REF: 04E803X0000 ☑CE (EMC), □ UL, □CE (LVD)